



AZ 50

DATASHEET

MIXER AMPLIFIER



DESCRIPTION

- Full digital technology mixer amplifier 160 w rms
- 100 v - 70 v outputs
- Presence control and per-channel high-pass filters

FEATURES

- Transformer System 160 watt Full Power
- 2x100 Watt Stereo with transformer Mixer Anfi
- 2 Microphone 1 Aux Input
- Independent Volume controller for All Inputs
- Independent Volume controller for 2 Zones
- Built in Bluetooth with Digital Fm Radio
- Adjusting microphone input volume.
- Ability to connect phone, computer, tablet with aux input.
- Usb Mp3 & Sd card input.
- Echo, Bass, Treble, Balance adjustment modes.
- Remote control
- 2 Zones Separate Audio
- Audio Source Input Mode Selector
- Microphone input 6.3 mm Jack
- Stereo Line In- and output (RCA)



AZ 50

DATASHEET

MIXER AMPLIFIER



Amplifier specifications	Number of channels	: 2
Power output (@ 100 V)		: 120 W RMS
Impedance		: 4ohm 8ohm
Frequency Response (-3dB)		: 20 Hz ÷ 20 kHz
THD		: <03%
Mic+Line inputs		: 2
Aux		: 1
Signal output number		: 2
Signal-to-noise ratio		: >85dB
Power Supply		: 220-240VAC 50Hz
DC power value		: 24 V
Power consumption		: 160 W
Accessories		: Power Cable Remote control
Dimensions (L x W x H)		: 200 x 330 x 65mm
Weight (kg)		: 3 kg